



TONE YOUR WAY



PLATINUM



PLATINUM

DESCRIPTION


- Full analog OD / preamp based on iconic Silver anniversary amp.
- Dual Channel mode, Clean / Rhythm & Lead mode, from clean and creamy crunch overdrive up to full throttle distortion for juicy solos.
- Unique Bass, Middle & Treble tone stack, just like the original amp, delivers versatile sonic capabilities.
- Presence switch functioning as a classic presence control by applying negative feedback, adjusts the dynamic response or boost upper frequencies.
- Parallel mode relay switching (True Bypass).

OPERATION

- Run a cable from your guitar to the Vs Audio "PLATINUM" INPUT jack and run another one from the Vs Audio "PLATINUM" OUTPUT jack to your amplifier.
- Start with all controls at 12 o' clock.
- Turn the effect on by pressing the footswitch. Parallel mode relay switching behaves like a standard footswitch plus the "HOLD-RELEASE" feature. On press and hold of the relay switch, instantly the effect turns on, on release of the switch, instantly the effect is bypassed.
- Rotate the OUTPUT MASTER knob clockwise or counter-clockwise to maintain unity volume with clean signal.
- Rotate the tone stack knobs (BASS, MIDDLE, TREBLE) clockwise to boost frequencies or counterclockwise to decrease them.
- Rotate the INPUT GAIN knob clockwise to increase the amount of gain or counter-clockwise to decrease it.
- Use the LEAD footswitch to toggle between CLEAN / RHYTHM and LEAD channel.

CONTROLS


- 1 **INPUT GAIN** controls the gain level of the clean/crunch of the Rhythm & Lead channel.
- 2 **PRESENCE** switch adjusts the "brightness" of the pedal in conjunction with Treble control.
- 3 **OUTPUT MASTER** controls the output of the effect.
- 4 **BASS** adjusts the low frequency content of the sound.
- 5 **MIDDLE** adjusts mid-range frequencies in the sound.
- 6 **TREBLE** adjusts the amount of upper frequencies in the sound.
- 7 **BYPASS** footswitch toggles effect on/bypass (red LED indicates on).
- 8 **LEAD** footswitch enables Lead Channel, the amount of gain applied to the Lead Channel



RED HOT JOHN



SMOKIN' JOE



LIFESON



POWER

The Vs Audio PLATINUM is powered by any voltage 9 volts DC, or any multi-power supply brick for effect pedals (recommended power supply output 9V DC 100mA, center negative polarity).

SPECIFICATIONS

Input Impedance	1M Ω
Output Impedance	<10k Ω
Noise Floor	-89dBV
Bypass	Silent True Relay Switched
Current Draw	60 mA
Power Supply	9V DC



VS AUDIO
4 MAVROMATEON Str, ILION
ATHENS, GREECE